

Update Notes for v Prog 6.4 & Boot 3.2c

WARNING

DO NOT run this update on a version 2.x PE as this will stop it working. A CPU upgrade is required which can be ordered from the Kiwitechnics web site.

NOTE

This update will remove PG-200 & PG-800 support. If you wish to use either of these patches do not put any update on the PE later than version 5.0. PEs with serial numbers higher than 1403 cannot support the PG-800 or PG-200 at all.

Also removed are Roland Juno-106, JX-8P, Oberheim M1000, M6r and MKS-30
Added are Kiwi1000 and Kiwi30

This update needs files to be run in the correct order.

Take note of the current release at normal power on. It will display PE x.x BL x.xy for a second at power on. The PE x.x is the current Program version and the BL x.xy is the current Bootloader version.

If the PE is below release number 4.2 you will first need to upgrade to version 5.0. Contact Kiwitechnics or join the Yahoo group for the files. There is a link on the Kiwi Home page to join.

- 1) Put the PE into update mode by pressing HPF button while powering on.
- 2) Play in the file PE_Boot_v32c_Build7.SYX
- 3) After the 'Update Successful' message press and hold the HPF button and cycle the power
- 4) Play in the file PE_Prog_v64_Build3.SYX
- 5) Cycle the Power